

WHAT IS CLAIMED IS:

1. An apparatus for detecting a power ratio between a first channel and a second channel in a mobile communication system, comprising:
 - 5 a channel estimator for generating a first signal by performing channel estimation using the first channel signal;
 - a channel compensator for generating a second signal by channel-compensating the second channel signal using the first signal; and
 - a power ratio detector for generating absolute values of symbols constituting
 - 10 the second signal, selecting absolute values in a predetermined length after sorting the absolute values in magnitude order, calculating an average value of the selected absolute values, calculating a square of an absolute value of the first signal, and generating the power ratio using a ratio of the average value to the square of the absolute value of the first signal.
 - 15
2. The apparatus of claim 1, wherein the power ratio detector comprises:
 - an absolute value generator for receiving symbols constituting the second signal and generating an absolute value of each of the symbols;
 - a sorter for sorting absolute values generated by the absolute value generator in
 - 20 magnitude order;
 - an average value calculator for selecting absolute values in a predetermined length among the sorted absolute values, and calculating an average value of the selected absolute values;
 - a squarer for calculating a square of an absolute value of the first signal; and
 - 25 a power ratio generator for generating the power ratio by a ratio of the average value to the square of the absolute value of the first signal.
3. The apparatus of claim 1, wherein the predetermined length is a length determined by separating the sorted absolute values into a predetermined number of
- 30 lengths centering on a preset reference point, selecting a length including a minimum value of the absolute values among the predetermined number of lengths, and selecting a preset length from the selected length.

4. The apparatus of claim 3, wherein the reference point is determined according to a modulation scheme of the second channel.

5 5. The apparatus of claim 3, wherein the preset length includes absolute values determined by excluding a preset number of absolute values among absolute values exiting in the selected length in descending order from a maximum value and a preset number of absolute values among the absolute values exiting in the selected length in ascending order from a minimum value.

10

6. An apparatus for detecting a power ratio between a first channel and a second channel in a mobile communication system, comprising:

an absolute value generator for receiving symbols constituting a first signal generated by channel-compensating the first channel signal;

15 a sorter for sorting absolute values generated by the absolute value generator in magnitude order;

an average calculator for selecting absolute values in a predetermined length among the sorted absolute values, and calculating an average value of the selected absolute values;

20 a squarer for calculating a square of an absolute value of a second signal generated by performing channel estimation using the second channel signal; and

a power ratio generator for generating the power ratio by a ratio of the average power to the square of the absolute value of the second signal.

25 7. The apparatus of claim 6, wherein the predetermined length is a length determined by separating the sorted absolute values into a predetermined number of lengths centering on a preset reference point, selecting a length including a minimum value of the absolute values among the predetermined number of lengths, and selecting a preset length from the selected length.

30

8. The apparatus of claim 7, wherein the reference point is determined according to a modulation scheme of the first channel.

9. The apparatus of claim 7, wherein the preset length includes absolute values determined by excluding a preset number of absolute values among absolute values existing in the selected length in descending order from a maximum value and a
5 preset number of absolute values among the absolute values existing in the selected length in ascending order from a minimum value.

10. An apparatus for detecting a power ratio between a first channel and a second channel in a mobile communication system, comprising:

10 a channel estimator for generating a first signal by performing channel estimation using the first channel signal;

a channel compensator for generating a second signal by channel-compensating the second channel signal using the first signal; and

a power ratio detector for generating absolute values of symbols constituting
15 the second signal, selecting absolute values in a predetermined length after sorting the absolute values in magnitude order, detecting a center value of the predetermined length, calculating a square of an absolute value of the first signal, and generating the power ratio using a ratio of the center value to the square of the absolute value of the first signal.

20

11. The apparatus of claim 10, wherein the power ratio detector comprises:

an absolute value generator for receiving symbols constituting the second signal, and generating an absolute value of each of the symbols;

25 a sorter for sorting absolute values generated by the absolute value generator in magnitude order;

a selector for selecting absolute values in a predetermined length among the sorted absolute values, and selecting a center value of the predetermined length;

a squarer for calculating a square of an absolute value of the first signal; and

30 a power ratio generator for generating the power ratio by a ratio of the center value to the square of the absolute value of the first signal.

12. The apparatus of claim 10, wherein the predetermined length is a length determined by separating the sorted absolute values into a predetermined number of lengths centering on a preset reference point, selecting a length including a minimum value of the absolute values among the predetermined number of lengths, and selecting
5 a preset length from the selected length.

13. The apparatus of claim 12, wherein the reference point is determined according to a modulation scheme of the second channel.

10 14. The apparatus of claim 12, wherein the preset length includes absolute values determined by excluding a preset number of absolute values among absolute values existing in the selected length in descending order from a maximum value and a preset number of absolute values among the absolute values existing in the selected length in ascending order from a minimum value.

15

15. An apparatus for detecting a power ratio between a first channel and a second channel in a mobile communication system, comprising:

an absolute value generator for receiving symbols constituting a first signal generated by channel-compensating the first channel signal, and generating an absolute
20 value of each of the symbols;

a sorter for sorting absolute values generated by the absolute value generator in magnitude order;

a selector for selecting absolute values in a predetermined length among the sorted absolute values, and selecting a center value of the predetermined length;

25 a squarer for calculating a square of an absolute value of a second signal generated by performing channel estimation using the second channel signal; and

a power ratio generator for generating the power ratio by a ratio of the center value to the square of the absolute value of the second signal.

30 16. The apparatus of claim 15, wherein the predetermined length is a length determined by separating the sorted absolute values into a predetermined number of lengths centering on a preset reference point, selecting a length including a minimum

value of the absolute values among the predetermined number of lengths, and selecting a preset length from the selected length.

17. The apparatus of claim 16, wherein the reference point is determined
5 according to a modulation scheme of the first channel.

18. The apparatus of claim 16, wherein the preset length includes absolute values determined by excluding a preset number of absolute values among absolute values existing in the selected length in descending order from a maximum value and a
10 preset number of absolute values among the absolute values existing in the selected length in ascending order from a minimum value.

19. An apparatus for detecting a power ratio between a first channel and a second channel in a mobile communication system, comprising:
15 a channel estimator for generating a first signal by performing channel estimation using the first channel signal;
a channel compensator for generating a second signal by channel-compensating the second channel signal using the first signal; and
a power ratio detector for generating absolute values of symbols constituting
20 the second signal, calculating an average value of the absolute values, calculating a $1/2$ value of the average value, and then generating the power ratio by a ratio of the $1/2$ average value to a square of an absolute value of the second signal.

20. The apparatus of claim 19, wherein the power ratio detector
25 comprises:

an absolute value generator for receiving symbols constituting the second signal and generating an absolute value of each of the symbols;
an $1/2$ average value calculator for calculating an average value of the absolute values and calculating a $1/2$ value of the average value;
30 a squarer for calculating a square of an absolute value of the first signal; and
a power ratio generator for generating the power ratio by a ratio of the $1/2$ average value to the square of the absolute value of the first signal.

21. An apparatus for generating a power ratio between a first channel and a second channel in a mobile communication system, comprising:

an absolute value generator for receiving symbols constituting a first signal
5 generated by channel-compensating the first channel signal;

a 1/2 average value calculator for calculating an average value of the absolute values and calculating a 1/2 value of the average value;

a squarer for calculating a square of an absolute value of a second signal generated by performing channel estimation using the second channel signal; and

10 a power ratio generator for generating the power ratio by a ratio of the 1/2 power value to the square of the absolute value of the second signal.

22. A method for detecting a power ratio between a first channel and a second channel in a mobile communication system, comprising the steps of:

15 generating a first channel signal by performing channel estimation using the first channel signal;

generating a second signal by channel-compensating the second channel signal using the first signal; and

generating absolute values of symbols constituting the second signal, selecting
20 absolute values in a predetermined length after sorting the absolute values in magnitude order, calculating an average value of the selected absolute values, calculating a square of an absolute value of the first signal, and generating the power ratio using a ratio of the average value to the square of the absolute value of the first signal.

25 23. The method of claim 22, wherein the predetermined length is a length determined by separating the sorted absolute values into a predetermined number of lengths centering on a preset reference point, selecting a length including a minimum value of the absolute values among the predetermined number of lengths, and selecting a preset length from the selected length.

30

24. The method of claim 23, wherein the reference point is determined according to a modulation scheme of the second channel.

25. The method of claim 23, wherein the preset length includes absolute values determined by excluding a preset number of absolute values among absolute values existing in the selected length in descending order from a maximum value and a
5 preset number of absolute values among the absolute values existing in the selected length in ascending order from a minimum value.

26. A method for detecting a power ratio between a first channel and a second channel in a mobile communication system, comprising the steps of:
10 generating an absolute value of each of symbols constituting a first signal generated by channel-compensating the first channel signal;
sorting the absolute values in magnitude order;
selecting absolute values in a predetermined length among the sorted absolute values, and calculating an average value of the selected absolute values;
15 calculating a square of an absolute value of a second signal generated by performing channel estimation using the second channel signal; and
generating the power ratio by a ratio of the average value to the square of the absolute value of the second signal.

20 27. The method of claim 26, wherein the predetermined length is a length determined by separating the sorted absolute values into a predetermined number of lengths centering on a preset reference point, selecting a length including a minimum value of the absolute values among the predetermined number of lengths, and selecting a preset length from the selected length.

25

28. The method of claim 27, wherein the reference point is determined according to a modulation scheme of the first channel.

29. The method of claim 27, wherein the preset length includes absolute
30 values determined by excluding a preset number of absolute values among absolute values existing in the selected length in descending order from a maximum value and a preset number of absolute values among the absolute values existing in the selected

length in ascending order from a minimum value.

30. A method for detecting a power ratio between a first channel and a second channel in a mobile communication system, comprising the steps of:

5 generating a first signal by performing channel estimation using the first channel signal;

generating a second signal by channel-compensating the second channel signal using the first signal; and

10 generating absolute values of symbols constituting the second signal, selecting absolute values in a predetermined length after sorting the absolute values in magnitude order, calculating a center value of the predetermined length, calculating a square of an absolute value of the first signal, and generating the power ratio using a ratio of the center value to the square of the absolute value of the first signal.

15 31. The method of claim 30, wherein the predetermined length is a length determined by separating the sorted absolute values into a predetermined number of lengths centering on a preset reference point, selecting a length including a minimum value of the absolute values among the predetermined number of lengths, and selecting a preset length from the selected length.

20

32. The method of claim 31, wherein the reference point is determined according to a modulation scheme of the second channel.

25 33. The method of claim 31, wherein the preset length includes absolute values determined by excluding a preset number of absolute values among absolute values existing in the selected length in descending order from a maximum value and a preset number of absolute values among the absolute values existing in the selected length in ascending order from a minimum value.

30 34. A method for detecting a power ratio between a first channel and a second channel in a mobile communication system, comprising the steps of:

generating an absolute value of each of symbols constituting a first signal

generated by channel-compensating the first channel signal;
 sorting the generated absolute values in magnitude order;
 selecting absolute values in a predetermined length among the sorted absolute values and selecting a center value of the predetermined length;
5 calculating a square of an absolute value of a second signal generated by performing channel estimation using the second channel signal; and
 generating the power ratio by a ratio of the center value to the square of the absolute value of the second signal.

10 35. The method of claim 34, wherein the predetermined length is a length determined by separating the sorted absolute values into a predetermined number of lengths centering on a preset reference point, selecting a length including a minimum value of the absolute values among the predetermined number of lengths, and selecting a preset length from the selected length.

15

 36. The method of claim 35, wherein the reference point is determined according to a modulation scheme of the first channel.

 37. The method of claim 35, wherein the preset length includes absolute
20 values determined by excluding a preset number of absolute values among absolute values existing in the selected length in descending order from a maximum value and a preset number of absolute values among the absolute values existing in the selected length in ascending order from a minimum value.

25 38. A method for detecting a power ratio between a first channel and a second channel in a mobile communication system, comprising the steps of:

 generating a first signal by performing channel estimation using the first channel signal;

 generating a second signal by channel-compensating the second channel signal
30 using the first signal; and

 generating absolute values of symbols constituting the second signal, calculating an average value of the absolute values, calculating a $1/2$ value of the

average value, and then generating the power ratio by a ratio of the $1/2$ average value to a square of an absolute value of the first signal.

39. A method for detecting a power ratio between a first channel and a
5 second channel in a mobile communication system, comprising the steps of:
- generating an absolute value of each of symbols constituting a first signal generated by channel-compensating the first channel signal;
 - calculating an average value of the absolute values and calculating a $1/2$ value of the average value;
 - 10 calculating a square of an absolute value of a second signal generated by performing channel estimation using the second channel signal; and
 - generating the power ratio by a ratio of the $1/2$ average value to the square of the absolute value of the second signal.